

Fluke 115 Digital Multimeter

Compact and easy to use 6000 count true RMS DMM, perfect for general purpose electrical & electronics troubleshooting

FLUKE®



Designed for Field Service Technicians

The Fluke 115 is the solution for a wide variety of electrical and electronic testing applications. This compact true-rms meter is for field service technicians as it provides an easy one-handed operation in a compact package.

It comes with a white large LED backlight to work in poorly lit areas with resistance, continuity functions and Min/Max/Average to record signal fluctuations. In addition it is CAT III 600V safety rated.

- Measure current upto 600 AC/DC and voltage upto 600V AC/DC, CAT IV 600V, CAT III 1000V safety rating
- Proprietary inrush measurement technology to capture motor starting current
- iFlex flexible current probe (sold separately) to expand measurement range upto 2500A AC

Specifications

AC/DC Voltage Measurement

Counts	6000
True-rms Readings	AC
Basic DC Accuracy	0.5%
Auto/Manual Ranging	•

Measurements

Voltage AC/DC	600 V
Current AC/DC	10 A
Resistance	40 MΩ
Frequency	50 kHz
Capacitance	10μF
Continuity with Beeper	•
Diode Test	•

Display

Analog Bargraph	•
Backlight	•

Warranty & Safety

Warranty	3 years
Dangerous Voltage Indication	•
EN61010-1 CAT III	600V